



**BALLASTS FOR COMPACT
FLUORESCENT LAMPS**
LOW LOSS

 Standard Cross-Section **28 x 41**

 Push-in terminal $\square 0,5 - 1 \text{ mm}^2$

 Screw terminal $0,5 - 2,5 \text{ mm}^2$
5 - 38W
230V / 50 Hz

VDE 0712 EN61347-60921 tw 130

MODEL	TYPE	LAMP			BALLAST						PHYSICAL CHARACTERISTICS			
		Wattage (W)	Current (A)	Cap	Inductive I	Temp. Dt/Dt _{an.}	EEI	Cp mF ±10% 250 V	Diagrams	 	DIMENSIONS		Weight (grs.)	Packing Units
											A (mm)	B (mm)		
ARC-P 09/23	FS 09 3012	1 x 5	0,180	G23	0,30	60/85	B2 B2 B1 B1	2	3	*	85	73,5	340	20
		1 x 7	0,175	G23	0,33				3					
		1 x 9	0,170	G23	0,38				3					
		1 x 11	0,155	G23	0,47				3					
ARC-P 13/23	FS 13 3012	1 x 10	0,190	G24d1	0,38	60/110	B2 B2 B2	2	3	*	85	73,5	340	20
		1 x 10	0,180	GR10q	0,45				5					
		1 x 13	0,175	G24d1/GX24d1	0,47				3					
		2 x 5	0,180	G23	0,38				4					
		2 x 7	0,160	G23	0,49				4					
		2 x 9	0,140	G23	0,57				4					
BPL 15/23	FD 15 3012	1 x 21	0,260	GR10q	0,45	55/95	B1	3	5	*	150	135	510	20
ARC-P 16/23	FS 16 3012	1 x 16	0,200	GR8/GR10q	0,46	60/140	B2	2	3-5	*	85	73,5	340	20
ARC-P 18D/23	FS 18 3012	1 x 18	0,220	G24d2/GX24d2	0,50	65/160	B2	2,5	3	*	85	73,5	340	20
BPL 18/23	FD 20 3012	1 x 18	0,375	2G10/2G11	0,32	60/125	B2 B2 B1	4,5	5	*	150	135	510	20
		1 x 24	0,340	2G10/2G11	0,41			4	5					
		1 x 26	0,315	G24d3/GX24d3	0,45			3,5	3					
ARC-P 26/23	FS 26 3012	1 x 26	0,315	G24d3/GX24d3	0,48	60/125	B2	3,5	3	*	110	98,5	500	20
BPL-P 26/23	FS 24/26 3011	1 x 24	0,345	2G10/2G11	0,42	60/120	B2 B1	4	5	*	110	98,5	500	20
		1 x 26	0,325	G24d3/GX24d3	0,46			3,5	3					
BPL-P 28/23	FS 28 3012	1 x 24	0,345	2G10/2G11	0,40	65/140	B2 B1 B1	4	5	*	110	98,5	500	20
		1 x 26	0,325	G24d3/GX24d3	0,45			3,5	3					
		1 x 28	0,320	GR8/GR10q	0,47			3,5	3-5					
BPL 36/23	FD 40 3011	1 x 36	0,430	2G10/2G11	0,46	50/145	B2	4,5	5	*	150	135	560	20
		2 x 18	0,400	2G10/2G11	0,48			6	6					
		1 x 38	0,430	GR10q	0,48			5	5					
BPL 36/23-2	FD 40 3015	1 x 36	0,430	2G10/2G11	0,46	55/155	B2	4,5	5	*	150	135	510	20
		2 x 18	0,400	2G10/2G11	0,48			6	6					
		1 x 38	0,430	GR10q	0,48			5	5					

Screw terminal on request

Other wattages, voltages and frequencies are available on request

