


**BALLASTS FOR COMPACT  
FLUORESCENT LAMPS**

 Standard Cross-Section **28 x 41**

 Push-in terminal  $\square 0,5 - 1 \text{ mm}^2$ 

 Screw terminal  $0,5 - 2,5 \text{ mm}^2$ 
**5 - 38W**
**230V / 50 Hz**
**VDE 0712 EN61347-60921 tw 130**

MODEL	TYPE	LAMP			BALLAST						PHYSICAL CHARACTERISTICS			
		Wattage (W)	Current (A)	Cap	Inductive I	Temp. Dt/Dtan.	EEI	Cp mF ±10% 250 V	Diagrams		DIMENSIONS		Weight (grs.)	Packing Units
											A (mm)	B (mm)		
ARC-P 09/23	FS 09 3012	1 x 5	0,180	G23	0,30	60/85	B2 B2 B1 B1	2	3	*	85	73,5	340	20
		1 x 7	0,175	G23	0,33				3					
		1 x 9	0,170	G23	0,38				3					
		1 x 11	0,155	G23	0,47				3					
ARC-P 13/23	FS 13 3012	1 x 10	0,190	G24d1	0,38	60/110	B2 B2 B2 - - -	2	3	*	85	73,5	340	20
		1 x 10	0,180	GR10q	0,45				5					
		1 x 13	0,175	G24d1/GX24d1	0,47				3					
		2 x 5	0,180	G23	0,38				4					
		2 x 7	0,160	G23	0,49				4					
		2 x 9	0,140	G23	0,57				4					
BPL 15/23	FD 15 3012	1 x 21	0,260	GR10q	0,45	55/95	B1	3	5	*	150	135	510	20
ARC-P 16/23	FS 16 3012	1 x 16	0,200	GR8/GR10q	0,46	60/140	B2	2	3-5	*	85	73,5	340	20
ARC-P 18D/23	FS 18 3012	1 x 18	0,220	G24d2/GX24d2	0,50	65/160	B1	2,5	3	*	85	73,5	340	20
ARC 18/23-c1	FD 20 3014	1 x 18	0,375	2G10/2G11	0,34	65/125	C B2 B1	4,5 4 3,5	5	*	150	135	510	20
		1 x 24	0,340	2G10/2G11	0,42				5					
		1 x 26	0,315	G24d3/GX24d3	0,48				3					
ARC-P 22/23	FS 28 3012	1 x 22	0,400	G10q	0,35	70/140	-	4,5	5	*	110	98,5	500	20
ARC-P 26/23	FS 26 3012	1 x 26	0,315	G24d3/GX24d3	0,48	60/125	B2	3,5	3	*	110	98,5	500	20
ARC 32/23	FC 32 3012	1 x 32	0,450	G10q	0,44	70/150	-	4,5	5	*	150	135	510	20
ARC 36/23-c1	FD 40 3012	1 x 36	0,430	2G10/2G11	0,48	65/165	C	4,5	5	*	150	135	510	20
		2 x 18	0,370	2G10/2G11	0,52				6					
		1 x 38	0,430	GR10q	0,48				5					
ARC 36/23-c2	FD 40 3010	1 x 36	0,430	2G10/2G11	0,48	60/155	C	4,5	5	*	150	135	560	20
		2 x 18	0,400	2G10/2G11	0,48				6					
		1 x 38	0,430	GR10q	0,48				5					

Screw terminal on request

Other wattages, voltages and frequencies are available on request

