

Halogenuros Metálicos - OSRAM

DENOMINACION	P _L (W)	In (A)	IL(A)	BALASTO LAYRTON	IG
HCI T 35	35	0,53	0,5	HSI-SAPI 35W	050
HCI TC 35	35	0,53	0,5	HSI-SAPI 35W	050
HCI T 70	70	1	1	HSI-SAPI 70W	050
HCI TC 70	70	1	1	HSI-SAPI 70W	050
HCI TT 70	70	1	1	HSI-SAPI 70W	050
HCI TS 70	70	1	1	HSI-SAPI 70W	050
HQI E 70	70	1	0,95-1	HSI-SAPI 70W	050
HQI T 70	70	1	1	HSI-SAPI 70W	050
HQI TS 70	70	1	1	HSI-SAPI 70W	050
HQI E 100	100	1,2	1,1	HSI-SAPI 100W	050
HCI T 150	150	1,8	1,8	HSI-SAPI 150W	050
HCI TT 150	150	1,8	1,8	HSI-SAPI 150W	050
HCI TS 150	150	1,8	1,8	HSI-SAPI 150W	050
HQI E 150	150	1,8	1,8	HSI-SAPI 150W	050
HQI R 150	150	1,8	1,8	HSI-SAPI 150W	050
HQI T 150	150	1,8	1,8	HSI-SAPI 150W	050
HQI TS 150	150	1,8	1,8	HSI-SAPI 150W	050
HCI E 250	250	3	2,9	HSI-SAPI 250W	051
HCI T 250	250	3	2,9	HSI-SAPI 250W	051
HCI TS 250	250	3	2,9	HSI-SAPI 250W	051
HQI E 250/N/SI	250	2,15	2,1	HIA-HSI 250W	020,051
HQI E 250	250	3	3	HSI-SAPI 250W	020,051
HQI T 250/N/SI	250	2,15	2,1	HIA-HSI 250W	020,051
HQI T 250	250	3	3	HSI-SAPI 250W	020,051
HQI TS 250	250	3	2,8-3	HSI-SAPI 250W	051
HQI BT 400	400	3,5	3,5	HIA-HSI 400W	051
HQI BT 400	400	4,2	4	HSI-SAPI 400W	051
HQI E 400/N/SI	400	3,5	3,25	HIA-HSI 400W	020,051
HQI E 400/D	400	3,5	3,6	HIA-HSI 400W	020,051
HQI E 400/D	400	4,2	3,8	HSI-SAPI 400W	051
HQI E 400/N	400	3,5	3,5	HIA-HSI 400W	051
HQI E 400/N	400	3,5	4,2	HSI-SAPI 400W	051
HQI T 400/N/SI	400	3,5	3,25	HIA-HSI 400W	020,051
HQI T 400/N	400	3,5	3,6	HIA-HSI 400W	051
HQI T 400/N	400	4,2	4,1	HSI-SAPI 400W	051
HQI T 400 BLUE	400	3,5	3,6	HIA-HSI 400W	051
HQI T 400 GREEN	400	3,5	3,6	HIA-HSI 400W	051
HQI T 400 RED MAGENTA	400	3,5	3,6	HIA-HSI 400W	051
HQI TS 400/D	400	3,5	3,6	HIA-HSI 400W	051
HQI TS 400/D	400	4,2	4,1	HSI-SAPI 400W	051
HQI TS 400/NDL	400	4,2	4	HSI-SAPI 400W	051
HQI T 1000	1000	9,5	9,5	HSI-SAPI 1000W	052
HQI TS 1000	1000	9,5	9,6	HSI-SAPI 1000W	052
HQI T 2000/D	2000	10.3	10,3	HSI 2000W/380V/10.3A	053
HQI T 2000/D/I	2000	10.3	10,3	HSI 2000W/380V/10.3A	no
HQI T 2000/N	2000	8.8	8,8	HSI 2000W/380V/8.8A	no
HQI T 2000/N/230V	2000	16.5	16,5	HSI 2000W	054

Halogenuros Metálicos - OSRAM

HQI T 2000/N/E SUPER	2000	8.8	8,8	HSI 2000W/380V/8.8A	053
HQI T 2000/N/SN/SUPER	2000	8.8	8,8	HSI 2000W/380V/8.8A	023,053
HQI TS 2000/D/S	2000	10,3	11,3	HSI-2000W/380V/10.3A	053
HQI TS 2000/N/L	2000	10,3	10,7	HSI-2000W/380V/10.3A	053

Halogenuros Metálicos - PHILIPS

DENOMINACION	P _L (W)	I _n (A)	IL(A)	BALASTO LAYRTON	IG
CDM-R 35	35	0,53	0,5	HSI-SAPI 35W	050
CDM-T 35	35	0,53	0,5	HSI-SAPI 35W	050
CDM-TC 35	35	0,53	0,5	HSI-SAPI 35W	050
CDM-ET 70	70	1	1	HSI-SAPI 70W	045
CDM-R 70	70	1	1	HSI-SAPI 70W	050
CDM-T 70	70	1	1	HSI-SAPI 70W	050
CDM-TC 70	70	1	1	HSI-SAPI 70W	050
CDM-TD 70	70	1	1	HSI-SAPI 70W	050
CDM-TP 70	70	1	0,98	HSI-SAPI 70W	050
CDM-TT 70	70	1	1	HSI-SAPI 70W	045
MHN-T 70W	70	1	0,99	HSI-SAPI 70W	050
MHN-TD 70W	70	1	0,98	HSI-SAPI 70W	050
MHW-TD 70W	70	1	0,98	HSI-SAPI 70W	050
CDM-T 150W	150	1,8	1,8	HSI-SAPI 150W	050
CDM-TD 150W	150	1,8	1,8	HSI-SAPI 150W	050
CDM-TP 150	150	1,8	1,8	HSI-SAPI 150W	050
CDM-TT 150	150	1,8	1,8	HSI-SAPI 150W	050
MHN-T 150	150	1,8	1,8	HSI-SAPI 150W	050
MHN-TD 150	150	1,8	1,8	HSI-SAPI 150W	050
MHW-TD 150	150	1,8	1,8	HSI-SAPI 150W	050
HPI Plus 250	250	2,15	2,2	HIA-HSI 250W	020,051
HPI Plus 250	250	3	2,55	HSI-SAPI 250W	020,051
HPI-T Plus 250	250	2,15	2,15	HIA-HSI 250W	020,051
HPI-T Plus 250	250	3	2,5	HSI-SAPI 250W	020, 051
MHN-TD 250W	250	3	3	HSI-SAPI 250W	051
HPI 400W Plus BUS	400	3,5	3,4	HIA-HSI 400W	no
HPI 400W Plus BUS	400	4,2	3,85	HSI-SAPI 400W	no
HPI Plus 400	400	3,5	3,4	HIA-HSI 400W	020, 051
HPI Plus 400	400	4,2	3,85	HSI-SAPI 400W	020, 051
HPI-T Plus 400	400	3,5	3,4	HIA-HSI 400W	020, 051
HPI-T Plus 400	400	4,2	3,8	HSI-SAPI 400W	020, 051
HPI-T 1000W	1000	8.25	8,25	HSI 1000W/8.25A	020, 052
MHN-LA 1000	1000	9,5	9,3	HSI-SAPI 1000W	052
MHN-SA 1800/400	1800	10,3	10,5	HSI 2000W/380V/10,3A	053
HPI-T 2000W/220	2000	16.5	16,5	HSI 2000W	020, 054
HPI-T 2000W/380	2000	8,8	8,6	HSI 2000W/380V/8.8A	053
MHN-LA 2000	2000	10,3	9,6	HSI 2000W/380V/10,3A	053
MHN-SA 2000	2000	10,3	11,3	HSI 2000W/380V/10,3A	053

Halogenuros Metálicos - GE

DENOMINACION	P _L (W)	In (A)	IL(A)	BALASTO LAYRTON	IG
CMH 35...	35	0,53	0,5	HSI-SAPI 35W	050
ARC 70/UVC...	70	1	0,95	HSI-SAPI 70W	050
ARC 70/T...	70	1	0,9	HSI-SAPI 70W	050
CMH 70...	70	1	0,98	HSI-SAPI 70W	050
CMH 100...	100	1,2	1,1	HSI-SAPI 100W	050
MXR 100	100	1,2	1,2	HSI-SAPI 100W	050
ARC 150/UVC...	150	1.8	1,8	HSI-SAPI 150W	050
ARC 150/T...	150	1.8	1,82	HSI-SAPI 150W	050
CMH 150...	150	1,8	1,8	HSI-SAPI 150W	050
MQI 250...	250	3	3	HSI-SAPI 250W	051
ARC 250/D/H/740	250	3	2,9	HSI-SAPI 250W	051
ARC 250/E...	250	3	2,9	HSI-SAPI 250W	051
ARC 250/T/H/742	250	3	2,75	HSI-SAPI 250W	051
ARC 250...	250	3	3	HSI-SAPI 250W	051
ARC 400	400	4,2	4,35	HSI-SAPI 400W	051
KRC 400...	400	3,5	3,5	HIA-HSI 400W	051
SPL 1000/D/H	1000	9,5	9,5	HSI-SAPI 1000W	052
SPL 2000/T/H	2000	10,3	10,3	HSI 2000W/380V/10,3A	053
SPL 2000/I/T/H	2000	10,3	10,3	HSI 2000W/380V/10,3A	no
SPL 2000/HR	2000	10,3	10,3	HSI 2000W/380V/10,3A	053

Halogenuros Metálicos - SYLVANIA

DENOMINACION	P _L (W)	I _n (A)	I _L (A)	BALASTO LAYRTON	IG
CMI-T	35	0,53	0,53	HSI-SAPI 35W	050
CMI-TC	35	0,53	0,53	HSI-SAPI 35W	050
CMI-T	70	1	0,98	HSI-SAPI 70W	045
CMI-TD	70	1	0,98	HSI-SAPI 70W	050
CMI-TC	70	1	0,98	HSI-SAPI 70W	050
HSI-MP	70	1	1	HSI-SAPI 70W	050
HSI-TD	70	1	0,98	HSI-SAPI 70W	050
HSI-T	70	1	0,95	HSI-SAPI 70W	050
HSI-MP	100	1,2	1,15	HSI-SAPI 100W	050
CMI-T	150	1,8	1,82	HSI-SAPI 150W	050
CMI-TD	150	1,8	1,82	HSI-SAPI 150W	050
HSI-MP	150	1,8	1,8	HSI-SAPI 150W	050
HSI-TD	150	1,8	1,8	HSI-SAPI 150W	050
HSI-T	150	1,8	1,82	HSI-SAPI 150W	050
HSI-TD	250	3	3	HSI-SAPI 250W	051
Britelux HSI-SX	250	3	2,9	HSI-SAPI 250W	051
Britelux HSI-TSX	250	3	2,9	HSI-SAPI 250W	051
HSI-HX 250W CO/I	250	2,15	2,1	HIA-HSI 250W	no
HSI-HX 250W	250	2,15	2,1	HIA-HSI 250W	020,051
HSI-THX	250	2,15	2,1	HIA-HSI 250W	020,051
Britelux HSI-SX	400	4,2	4,4	HSI-SAPI 400W	051
Britelux HSI-TSX	400	4,2	4,4	HSI-SAPI 400W	051
HSI-HX 400W CO/I	400	3,5	3,4	HIA-HSI 400W	no
HSI-HX 400W	400	3,5	3,4	HIA-HSI 400W	020,051
HSI-THX	400	3,5	3,4	HIA-HSI 400W	020,051
HSI-T	1000	8,25	8,25	HSI-1000W(8,25A)	020,052
HSI-T 2000W 380V/I	2000	8,8	9	HSI 2000W/400V/8,8A	no
HSI-T 2000W	2000	8,8	9	HSI 2000W/400V/8,8A	053
HSI-TD	2000	10,3	11,3	HSI 2000W/400V/10,3A	053