

**BALLASTS A DEMARRAGE  
RAPIDE HAUTE FACTEUR**

**20 - 65W**  
**230V / 50 Hz**

**RSAF ( Semiresonat, lampe )**
**EN 60920-60921 tw 130**

| TYPE       | BALLAST            |                    |        |                        |                                      |         | LAMPE               |               |       | CARACTERIS. PHISIQUES |             |                   |                   |
|------------|--------------------|--------------------|--------|------------------------|--------------------------------------|---------|---------------------|---------------|-------|-----------------------|-------------|-------------------|-------------------|
|            | LAMPE              |                    | V / Hz | Inductive<br>$\lambda$ | Temp.<br>$\Delta t / \Delta t_{an.}$ | Schemas | Dimension<br>( mm ) | $\varnothing$ | Culot | DIMENSIONS            |             | Poids<br>( grs. ) | Pieces<br>Embaees |
|            | Puissance<br>( W ) | Intensite<br>( A ) |        |                        |                                      |         |                     |               |       | A<br>( mm )           | B<br>( mm ) |                   |                   |
| RSAF 20/23 | 20                 | 0,370              | 230/50 | 0,90                   | 60/140                               | 8       | 590                 | 38            | G13   | 245                   | 140         | 950               | 20                |
| RSAF 40/23 | 40                 | 0,430              | 230/50 | 0,90                   | 55/140                               | 8       | 1200                | 38            | G13   | 245                   | 140         | 950               | 20                |
| RSAF 65/23 | 65                 | 0,670              | 230/50 | 0,90                   | 65/150                               | 8       | 1500                | 38            | G13   | 245                   | 140         | 1100              | 20                |

D'autres tensions au frequences sur demande

